

CLASSE

SIGMA SERIES

Sigma SSP

surround sound preamp/processor



Modern high-end audio systems tend to fall into one of two broad categories: stereo and theater. But rarely are they used exclusively in those roles. Most have a television display of some kind between stereo speakers or use the surround sound system for playing music. Inevitably, each makes compromises as it tries to accommodate the requirements of the other.

The Sigma SSP is designed to build a bridge between these two categories, optimized as a stereo preamp/processor but with HDMI switching and 7.1 channels of high-performance multichannel processing included. The stereo preamp/processor circuitry is derived from the latest generation Delta series CP-800, making the Sigma SSP a stunning performer as a stereo preamp. Test bench measurements are exceptional and suggest comparison with cost-no-object designs. Sonically the Sigma SSP out-performs stereo preamps with stand-alone DACs, while offering superb decoding of high-resolution formats including Dolby TrueHD and DTS-HD Master Audio.

A variety of connection options supports virtually any source optimally: Stream audio asynchronously from a computer, storage device or the Internet via the Sigma SSP's Ethernet connection. The Sigma SSP supports both AirPlay and DLNA streaming. Front and rear panel USB connections support asynchronous streaming from computers and iOS devices. Eight HDMI inputs (including one on the front panel) provide the optimum path for Blu-ray players, games and set-top boxes while simplifying



The Audio Return Channel lets other online sources decoded through the Sigma SSP by using the Ethernet. Coax and optical are also lacking the HDMI option.

DSP options for improving performance are available to all sources. Bass management, a nine-band Parametric EQ and digital domain Tone Control with our Tilt feature ensure that the system can be optimized for your speakers and room, and every source sounds its best. An optional phono stage with custom loading may be fitted to accommodate MM and MC cartridges.

The Sigma SSP owes its outstanding performance and value to the unique engineering and manufacturing capabilities of Classé in Montréal and the B&W Group globally. No other high-end audio designers have access to the resources necessary to deliver such a product at such a competitive price. The Sigma SSP has been conceived and built as an example of quality and value without peer. It will stand as the seminal reference in the preamp/processor category for many years to come.

Optimized using
trial version
www.balesio.com

CLASSE

SIGMA SERIES

Sigma SSP surround sound preamp/processor



Sigma SSP Specifications

USB audio	up to 24-bit/192 kHz
USB (Host)	charging capability 2 Amps
AirPlay supported formats	AAC (8 to 320 kbps) Protected AAC (from iTunes Store), HE-AAC, MP3 (8 to 320 kbps), MP3 VBR, Audible (formats 2, 3, 4) Audible Enhanced Audio (AAX, and AAX+), Apple Lossless, AIFF, and WAV
DLNA supported formats	Apple Lossless (ALAC), mp3, FLAC, WAV, Ogg Vorbis, WMA, AAC
Frequency response	8 Hz - 200 kHz < 1 dB, stereo digital bypass 8 Hz - 20 kHz < 0.5 dB, all other sources
Channel Matching (Left to Right)	better than 0.05 dB
Distortion (THD+noise)	0.0005%, digital source/bypassed analog source .002%, processed analog source
Maximum input level (single-ended)	2 Vrms (DSP), 4.5Vrms (bypass)
Maximum input level (balanced)	4 Vrms (DSP), 9 Vrms (bypass)
Maximum output level (single-ended)	9 Vrms
Maximum output level (balanced)	18 Vrms
Gain Range	-93 dB to +14 dB
Input impedance (single-ended)	100 kΩ (single-ended)
Input impedance (balanced)	50 kΩ (Balanced)
Output impedance (single-ended)	100 Ω
Output impedance (balanced)	300 Ω
	104 dB, bypassed analog source 101 dB, processed analog source (re. full-scale input, unweighted) 105 dB, digital source
	better than 100 dB



Optimized using
trial version
www.balesio.com

change.
physical errors.
lock.

Channel matching (left to right)	>0.05 dB
Crosstalk (any input to any output)	better than -130 dB @ 1 kHz
Rated power consumption	35 W
Mains voltage	100-240 V, 50/60 Hz
Overall dimensions	Width: 17.0" (433mm) Depth (excluding connectors): 14.57" (370mm) Height: 3.75" (95mm)
Net weight	18 lb (8.21 kg)
Shipping weight	25 lb (11.34 kg)
Made for	
iPod touch (5th generation)	iPod nano (7th generation)
iPod touch (4th generation)	iPod nano (6th generation)
iPod touch (3rd generation)	iPod nano (5th generation)
iPod touch (2nd generation)	iPod nano (4th generation)
iPod touch (1st generation)	iPod nano (3rd generation)
Made for	
iPhone 5S	iPhone 3GS
iPhone 5	iPhone 3G
iPhone 4S	iPhone
iPhone 4	
Made for	
iPad mini (with Retina display)	iPad (3rd generation)
iPad Air	iPad 2
iPad (4th generation)	iPad
iPad mini	
Airplay	
AirPlay works with iPhone, iPod, and iPod touch with iOS 4.3.3 or later, Mac with OS X Mountain Lion, and Mac and PC with iTunes 10.2.2 or later.	



USA & Canada • B&W Group Canada, Ltd.
5070 François Cusson • Lachine • Québec • Canada • H8T 1B3
Tel +1.514.636.6384 • Fax +1.514.636.1428
www.classeaudio.com • email: cservice@classeaudio.com