

Essential II DIGITAL

„Best Buy“ turntable with MM pre-amp + OPTICAL OUTPUT

- Ideal for connection to multiroom systems (SONOS, HEOS etc) or TVs, soundbars and portable audio
- Perfect solution if only a digital input is available
- Easy set-up
- Belt drive with silicone belt and low vibration motor
- 8,6" aluminium tonearm with sapphire bearings
- Ortofon OM5e cartridge pre-mounted
- Built-in phono pre-amplifier with analogue & digital out
- Gold-plated RCA interconnect cable included
- Special turntable feet for effective decoupling
- High-gloss colour options: Black, White, Red

Speed	33, 45 (manual speed change)
Principle	belt drive
Speed variance	33: 0,14% 45: 0,25%
Wow & flutter	0,12%
Platter	300mm particle board & felt mat (0,8kg)
Main bearing	stainless steel
Tonearm	8,6" aluminium
Effective arm length	218,5 mm
Overhang	22,0mm
Effective tonearm mass	8,0gr
Counterweight for mass	3 - 5,5g (included)
Tracking force range	0 - 25mN (OM5 18mN recommended)
Line output voltage typically	160mV/1kHz at 4mV/1kHz input
Noise floor	>73dB
RIAA-equalisation accuracy	20Hz-20kHz / max. 0,5dB
Optical output	24/96 kHz (bit depth/sampling frequency)
Included accessory	power supply, dust cover
Power consumption	4,5 watts
Dimensions	420 x 112 x 330mm (WxHxD)
Weight	4,0 kg net



Essential II DIGITAL
SRP
379,00 €

Turntable innovation with DIGITAL OPTIC and line output!

Many new audio systems, like home cinema receivers, soundbars, multiroom audio, TVs and Bluetooth speakers only offer digital optic input connections: So up to now vinyl lovers using such systems had no chance to play their records on those systems. **The perfect solution is: Essential II DIGITAL**

An unique belt-drive turntable with built-in MM pre-amplifier that features **digital optic** as well as **analogue** amplifier connection options. Delivered with acrylic lid and with black, white and red high-gloss colour options.

